

AOR Manufacturing Ltd, 4E East Mill, Bridgefoot, Belper, Derbyshire DE56 2UA, England
Tel: +44 1773 880788 Fax: +44 1773 880780 info@aor.co.uk www.demon.co.uk/aor

AR7030 infrared control information:

NEC protocol 16 bit
Address 026 HEX

I.R key	Hex value
1	0C
2	11
3	12
4	10
5	19
6	1A
7	18
8	1D
9	1E
0	15
. DECIMAL	16
CLEAR	13
BACKSPACE	1C
kHz	17
MHz	1F
CW/NFM	8
LSB/USB	0D
AM/SYNC	0E
+ MODIFY	2
- MODIFY	6
TUNE UP	3
TUNE DOWN	7
VOLUME UP	0B
VOLUME DOWN	0F
PASSBAND MODIFY	0
FILTER MODIFY	1
BASS MODIFY	5
TREBLE MODIFY	14
VFO SELECT A/B	0A
MEMORY STORE	4
MEMORY PREVIEW	9
MEMORY RECALL	1B
•	